



### Features

- **Zone Control Circuits**

Speaker zones can be selected individually by means of the CHANNEL switches or altogether using the All Call switch.

- **Announcements by Microphone**

Unobtrusive and easy to use condenser type microphone which is highly sensitive and reproduces high clarity speech. Paging is initiated by pressing the TALK switch.

- **Pre-Announcement Chime**

A four tone chime is incorporated for pre-announcement purposes. It is initiated by pressing the CHIME switch.

- **Auxiliary Input for Increased Versatility**

The auxiliary input can be used for a wide range of signal sources such as cassette deck or tuner, making it the ideal solution for broadcasting background music or radio to the power amplifier.

- **LED Output Level Indication**

The ten segment LED barograph display indicates the instantaneous signal output level of the amplifier. Any excessive input to the amplifier can therefore be monitored and adjusted as necessary.

# RM-5116 Architects and Engineers Specifications

## Technical Specifications

<b>ELECTRICAL</b>	<b>RM-5116</b>
Output Level/Impedance	1V/600Ω, Bal
Input Sensitivity/Impedance	
Mic	1mV/600Ω
Aux	300mV/10kΩ
Frequency Response(-3dB)	20Hz ~20kHz
T.H.D	Less than 0.2%
S/N	Better than 60dB
Speaker Control Terminal & Switch	16 CH
<b>GENERAL</b>	
Power Source	24VDC
Weight	1.2kg
	2.6lbs
Dimensions mm	232 x 53 x 200
(W x H x D) inch	9.6" x 2.3" x 8"



OFFICE : 1F, 318-4, Yatap-dong, Bundang-gu, Seongnam-city, Gyeonggi-do, South Korea.  
 TEL: 82-31-704-3050, FAX: 82-31-704-3056, www.kodio.co.kr E-MAIL: joseph@dsk.or.kr