

VISTA-12D

Control Panel

Honeywell's VISTA-12D is a six-zone control panel designed to address security dealers' most important needs. It significantly reduces dealer training and service call costs thanks to user-friendly features that make operation easier than ever, and offers increased upsell opportunities through its expansion capabilities and flexibility.



The feature-rich panel is the industry's most economical control and is ideally suited for a wide range of applications.

Features

- 2 partitions + 1 common partition
- 22 protection zones + 16 keyfob zones
- 6 basic hardwired zones with optional zone-doubling of each zone and optional fast respond times 10mSec
- 16 wireless expansion zones
- 8 additional wired zones using 8-zone 4219/4229 modules
- 254 Event log
- 16 user codes
- Four configurable zone type allows installers to create their own custom zone type

- Two on-board triggers
- Four output devices using a 4204 relay module

Valuable End-User Features

- Flexible function keys allow single button arming
- Two programmable macro key
- Viewable on system keypad display
 - Exit countdown
 - Time and date*
 - Event log*

- Eight schedules
 - Can activate relays on programmed times or on events
 - Latchkey reports to a pager
 - "User Access" time windows
- Chime by zone
- Telecommand Voice Module allows system control from any touchtone phone
- Four output devices with multiple actions per device
 - Turn lights on when system disarms with a 4204 relay
 - Flash same lights when system is in alarm using a 4204 relay

* Requires custom alpha keypad

VISTA-12D

Control Panel

Specifications:

Electrical:

- Aux power 12VDC, 600mA max
- Seven hour standby at 400 mA aux load with four amp hour battery
- 16.5VAC/25VA transformer
- Alarm output 12VDC, 2.0 amps max
- Battery: 12VDC, 4AH minimum
- Fuse: Battery (3A)

Output Control:

- Supports multiple output devices, one 4204 and two triggers

Zones:

- Six hardwired zones with zone doubling
- Selectable response: 10msec, 400msec, 700msec, 1.2 seconds
- 23 selectable zone types plus 4 configurable zone type
- Programmable swinger suppression

Expansion Devices:

- 4204 - Up to four relays - 15mA standby (each active relay draws an additional 40mA)

Accessories:

- Telecommand Voice Module - 119mA
- 5881ENH supports up to 16 zones - 50mA,
- 4229 Zone Expand/Relay Unit 35-100mA
- 4219 Zone Expander : 35mA
- 4204 Four-Relay Module : 15-180mA

Keypads:

- 6160 Custom Alpha (required for programming) - 100mA
- 6150RF Fixed English RF LCD - 85mA/40mA
- 6148 Fixed English LCD - 70mA/30mA

Smoke Detectors:

- Supports four-wire smoke detectors

Communications:

- Touchtone or pulse
- Formats supported
 - ADEMCO Contact ID
 - ADEMCO Express
 - ADEMCO low speed
 - Sescoa/Radionics
 - Robofon Contact ID
- Reporting capabilities
 - Split
 - Dual
 - Split/Dual - True dial tone detection
- Low battery reports 11.2 - 11.6VDC
- AC loss and restoral reporting supported

Ordering:

VISTA-12DLCT	Control Panel PCB only
VISTA-12D	Control Panel
6160	English LCD Keypad
6148	Fixed English LCD Display
4204	Four-Relay Module
Telecommand	Phone Access Module
4219	Console line 8 Zone Expander
4229	8 Zone Expander with 2 Relay output

For more information:

Australia	Tel: (61) 1300 368 755	Korea	Tel: (82) 2-799 6130
China	Tel: (86) 755-8299 5168	Singapore	Tel: (65) 6333 9563
Hong Kong	Tel: (852) 2405 2323	Taiwan	Tel: (886) 2-2245 1000
India	Tel: (91) 11-5239 9900		

www.security.honeywell.com
security.ap@honeywell.com

Automation & Control Solutions

Honeywell Security - Asia Pacific
Honeywell International Inc.
www.honeywell.com

VISTA12DAP0305
©2004 Honeywell International Inc.

Honeywell